

- N. B. :** (1) Question No. 1 is **compulsory**.  
 (2) Solve any **three** questions out of remaining **five**.

1. (a) Define the following terms :- 10
  - (i) Foreign key
  - (ii) Derived attribute
  - (iii) Deadlock
  - (iv) Schedule
  - (v) Data Independence
- (b) Suppose that we decompose the schema 5  
 $R = \{A, B, C, D, E\}$  into  
 $R_1 = \{A, B, C\}$  and  
 $R_2 = \{A, D, E\}$   
 Show that this decomposition is lossless join decomposition if the following set of functional dependencies hold  
 $A \rightarrow BC$        $CD \rightarrow E$   
 $B \rightarrow D$        $E \rightarrow A$
- (c) Explain Generalization and Specialization. 5
2. (a) What are triggers? Explain with example. 10
- (b) Explain advantages of DBMS over file system. 10
3. (a) Draw E-R diagram for university database consisting of four entities: Student, department, class, faculty. Student has a unique id, the student can enroll for multiple classes and has at most one major. Faculty must belong to department and faculty can teach multiple classes. Each class is taught by only one faculty. Every student will get grade for the class he/she has enrolled. 10
- (b) Explain serializability with example. 10
4. (a) Consider Insurance Database given below and answer the following queries in SQL. 10  
 Person (driver\_id, name, address)  
 Car (license, model, year)  
 Accident (report\_no, adate, location)  
 Owns (driver\_id, license)  
 Participated (driver\_id, license, report\_no, damage\_amount)  
 (1) Find total number of people who owned cars that are involved in accidents in 2004.

- (2) Find the number of accidents in which car belonging to 'John Smith' were involved.
- (3) Add new accident to Database.
- (4) Delete 'Santro' belonging to 'John Smith'.
- (b) List the ACID properties. Explain usefulness of each. **10**
5. (a) Consider the following relation **10**  
CAR-SALE (Car#, Date-sold, Salesman#, commission%, Discount-amt)  
Assume that {Car#, Salesman#} is the primary key. Additional dependencies are  
Date-sold → Discount-amt  
Salesman# → commission%  
Based on the given primary key, is this relation in 1NF, 2NF or 3NF? Why or why not? How would you successively normalize it completely?
- (b) Explain concurrency control in database system with the help of only two protocols. **10**
6. (a) Explain any four relational algebra operations with proper examples. **10**
- (b) Draw a query tree for the following SQL query **10**  
Select P. Pnumber, P.Dnum, E.Lname, E.Address, E.Bdate from project as P,  
Department as D, Employee as E where P.Dnum = D.Dnumber  
and D.Mgr-ssn = E.ssn  
and P. Plocation = 'Mumbai'
-

(3 Hours)

[ Total Marks :80]

N.B. : (1) Question no. 1 is compulsory.

(2) Attempt any three questions from remaining five questions.

(3) Assume suitable data if required

1. Solve any five

20

- (a) Convert  $(41.62)_8$  to decimal, binary and hexadecimal
- (b) Compare BJT and FET.
- (c) Why Zener diode is used as a regulator?
- (d) Define (i) Slew rate (ii) CMRR. What are the typical values of slew rate and CMRR for Op-amp IC- 741?
- (e) Convert JK-flip flop to D flip flop
- (f) What do you mean by Universal gate? Implement Ex-OR gate using NAND gate.

2. (a) What is the need of biasing? Explain Voltage divider bias and locate Q point.

10

(b) Design half adder using VHDL.

5

(c) Simplify  $AB + B + \overline{AC} + A\overline{BC} (AB + C)$ 

5

$$AB + B + \overline{AC} + A\overline{BC} (AB + C)$$

3. (a) Minimize the following Boolean function using K-map

10

$$F(A, B, C, D) = \sum m(0, 3, 7, 11, 15) + d(1, 2, 5)$$

5

(b) Explain Differentiator using Op-amp

5

(c) Explain the working of Liquid Crystal display.

4. (a) Design and implement 4 bit binary to gray code converter.

10

(b) Implement  $F(A, B, C, D) = \sum m(1, 2, 5, 11, 14) + d(0, 3)$  using 8:1 multiplexer.

5

(c) Explain inverting amplifier using Op-amp. Derive expression for output voltage.

5

5. (a) Explain the working of astable multivibrator using IC-555. Design astable multivibrator for output frequency 5KHz and duty cycle 30%.

10

(b) Differentiate between combinational and sequential logic circuits.

5

(c) Design mod-3 up counter using JK flip-flop

5

6. Write notes on Any four :-

20

(a) Instrumentation amplifier using 3-OP-Amps.

(b) Shift registers.

(c) Race around condition.

(d) Current mirror circuit.

(e) Multiplexers and De multiplexers.

**QP Code :14620**

(3 Hours)

[Total Marks : 80

- N.B. :** (1) Question No. 1 is compulsory.  
 (2) Attempt any **three** out of **remaining**.  
 (3) **Figures to right** indicate **full** marks.

1. (a) Explain big O notation. 3  
 (b) Consider the following recursive function that takes two arguments 3

```
int foo( int n, int r)
{
    if (n > 0)
        return ((n% r) + foo( n / r, r));
    else
        return 0;
}
```

What is the return value of the function foo when it is called as foo (65, 2) ?

- (c) What is a queue ? Specify ADT for it. 3  
 (d) What is linked list ? State the different types of linked list. 3  
 (e) Write down properties of Red-Black tree. 3  
 (f) Define a graph. Which are the methods to represent a graph ? 3  
 (g) Define minimum spanning tree. State the techniques to compute minimum spanning tree. 2

2. (a) Explain Quick sort using an example. 10  
 Write algorithm for it and comment on its complexity.  
 (b) Define double ended queue. Specify ADT for it. Implement any 2 operations of it. 10

3. (a) Construct the binary tree for the inorder and postorder traversal sequence given below :--

Inorder "INFORMATION"

Postorder "INOFMAINOTR"

Write a function to traverse a tree in postOrder.


- (b) Convert following infix expression into prefix and postfix format. 10

$(a*b - (c + d / e ^ f) - g) * h$

Write an algorithm Conversion() to convert infix expression into postfix expression.

[TURN OVER

4. (a) Write a program for implement array based Queue? List its applications. 10  
 (b) Sort the following data in descending order using Heap Sort. 10  
 20, 14, 50, 3, 5, 7, 11, 8, 12, 15  
 Show all the steps.  
 Write an algorithm for heap sort.
5. (a) What is an AVL tree ? Construct AVL tree for following data. [Mention the type of rotation for each case.] 10  
 1, 2, 3, 4, 8, 7, 6, 5, 11, 10, 12.  
 (b) Write functions to implement insert() and traverse() of singly inked list. 10
6. (a) Draw the minimum cost spanning tree using Kruskal's algorithm. Also find its cost with all intermediate steps. 10



- (b) Explain Binary search tree with an example. 5  
 (c) Write an algorithm for DFS traversal. 5

(3 Hours)

[ Total Marks : 80

- N. B. :** (1) Question No.1 is compulsory.  
 (2) Assume suitable data if required.  
 (3) Solve any three out of remaining questions.

1. Solve any four: 20
  - (i) Explain types of communication channels?
  - (ii) Compare ASK, PSK, FSK modulation techniques?
  - (iii) Explain- Fidelity
  - (iv) What is quantization?
  - (v) What is Image Frequency and its rejection?
  
2. (a) Explain the operating principal, working of Differentially Encoded Phase Shift Keying modulator and demodulator? 10
- (b) A sinusoidal carrier has an amplitude of 10v and a frequency of 100KHZ. It is amplitude modulated by a sinusoidal voltage of amplitude 3v and frequency 500HZ. Modulated voltage is developed across 75  $\Omega$  resistance: 10
  - (i) Write the equation for modulated wave.
  - (ii) Determine the modulation index.
  - (iii) Draw spectrum of modulated wave.
  - (iv) Calculate the total average power.
  - (v) Calculate the power carried by sidebands.
  
3. (a) Explain the block diagram of analog and digital communication system? If information rate is maximum which type of modulation technique can be used? 10
- (b) What is probability of error and Bandwidth requirement for BPSK? 10
  
4. (a) Explain sampling theorem for bandpass signals with proof. And also explain anti-aliasing filter? 10
- (b) Explain Armstrong method for FM generation? 10
  
5. (a) Explain PPM generation and degeneration method? 8
- (b) Write fourier Transform of Unit step, Delta and gate function? 8
- (c) What is eye pattern? 4
  
6. (a) Write short notes on (any four) 20
  - (i) Multiplexing Techniques
  - (ii) Noise Figure and Noise Factor
  - (iii) Pre-emphasis and De-emphasis
  - (iv) Line codes
  - (v) M-ray Phase Shift Keying

(3 Hours)

[ Total Marks :80

- N.B. : (1) Question No.1 is **compulsory**.  
 (2) Attempt any **three** from remaining.

1. (a) Write a program that queries a user for the no.: of rows and columns representing students and their marks. 10

Reads data row by row and displays the data in tabular form along with the row totals, column totals and grand total

Hint : For the data 1, 3, 6, 7, 9, 8 the output is

1	3	6		10
7	9	8		24
8	12	14		34

- (b) Explain System.arraycopy ( ) 5
- (c) Explain multiple inheritance in java with suitable example. 5
2. (a) Identify classes and their attributes and draw the relationships that are described by the following business rules. Include the multiplicities for each relationship. 12
- (i) A patient must be assigned to only one doctor and a doctor can have one or many patients.
  - (ii) An employee has one phone extension and unique phone extension is assigned to an employee.
  - (iii) A movie theatre shows atleast one movie and a movie can be shown at upto 4 other movie theatres around town.
  - (iv) A movie either has one star, 2 co-stars or more than 10 people starring together. A star must be in atleast one movie.
- (b) Explain coupling and cohesion with suitable example. 8
3. (a) Each year, sleepy Hollow Elementary school holds a "Principal for a Day" lottery. A student can participate by entering his/her name and ID into a pool of candidates. The winner is selected randomly from all entries. Each student is allowed one entry. Implement a student class that encapsulates a student. Implement StudentLottery class with methods addStudents () and pickwinner () and main () Hint : Use Random class to pick winner. 10

- (b) With suitable example, explain creation and use of user defined packages. 10
- 4.(a) Write detailed note on following exception handling terms. 10
- (i) try-catch
  - (ii) finally
  - (iii) Catch multiple exception
  - (iv) Throwing exception.
- (b) Write a program that computes the sum of a list of integers that is supplied by a user. The end of data signalled by the value - 999. This value is used only as a flag and not used in sum. 10
5. (a) Create Rectangle and Cube class that encapsulates the properties of a rectangle and cube i.e. Rectangle has default and parameterised constructor and area () method. Cube has default and parameterised constructor and volume () method. They share no ancestor other than Object. 15
- Implement a class Size with size() method. This method accepts a single reference argument z. If z refers to a Rectangle then size (z) returns its area and if z is a reference to a Cube, then size (z) returns its volume. If z refers to an object of any other class, then size (z) returns - 1. Use main () method in Size class to call size (..) method.
- (b) Differentiate between Interface and abstract class. 5
6. Write short notes on any **four** :- 20
- (a) JVM
  - (b) Package
  - (c) Polymorphism
  - (d) Wrapper class
  - (e) ArrayList and LinkedList
  - (f) Vector.
-



**QP Code : 14544**

**[3 Hours]**

**[ Total Marks: 80**

**N.B.** (1) Question no. 1 is compulsory.

(2) Attempt any three from the remaining.

(3) **Figures** to the **right** indicate **full** marks.

1. (a) Find the Laplace Transform of  $\sin t \cos 2t \cos ht$ . 5  
(b) Find the Fourier series expansion of  $f(x) = x^2$   $(-\pi, \pi)$  5  
(c) Find the z-transform of  $\left(\frac{1}{3}\right)^{|k|}$  5  
(d) Find the directional derivative of  $4xz^2 + x^2yz$  at  $(1, -2, -1)$  in the direction of  $2\bar{i} - \bar{j} - 2\bar{k}$  5
2. (a) Find an analytic function  $f(z)$  whose real part is  $e^x(x \cos y - y \sin y)$  6  
(b) Find inverse Laplace Transform by using convolution theorem  $\frac{1}{(s-3)(s+4)^2}$  6  
(c) Prove that  $\bar{F} = (6xy^2 - 2z^3)\bar{i} + (6x^2y + 2yz)\bar{j} + (y^2 - 6z^2x)\bar{k}$  is a conservative field. 8  
Find the scalar potential  $\phi$  such that  $\nabla \phi = \bar{F}$ . Hence find the workdone by  $\bar{F}$  in displacing a particle from  $A(1,0,2)$  to  $B(0,1,1)$  along  $AB$ .
3. (a) Find the inverse z-transform of  $F(z) = \frac{z^3}{(z-3)(z-2)^2}$  6  
(i)  $2 < |z| < 3$  (ii)  $|z| > 3$   
(b) Find the image of the real axis under the transformation  $w = \frac{2}{z+i}$  6  
(c) Obtain the Fourier series expansion of 8  
 $f(x) = \pi x; 0 \leq x \leq 1$   
 $= \pi(2-x); 1 \leq x \leq 2$   
Here deduce That  $\frac{1}{1^2} + \frac{1}{3^2} + \dots = \frac{\pi^2}{8}$
4. (a) Find the Laplace Transform of 6  
 $f(t) = E; 0 \leq t \leq \frac{p}{2}$   
 $= -E; \frac{p}{2} \leq t \leq p, \quad f(t+p) = f(t)$

**[ TURN OVER**

(b) Using Green's theorem evaluate  $\int_c \frac{1}{y} dx + \frac{1}{x} dy$  where  $c$  is the boundary of the region bounded by  $x=1$ ,  $x=4$ ,  $y=1$ ,  $y=\sqrt{x}$  6

(c) Find the Fourier integral for  $f(x) = 1-x^2$ ,  $0 \leq x \leq 1$   
 $= 0$   $x > 1$  8

Hence evaluate  $\int_0^{\infty} \frac{\lambda \cos \lambda - \sin \lambda}{\lambda^3} \cos\left(\frac{\lambda}{2}\right) d\lambda$

5. (a) If  $\vec{F} = x^2\vec{i} + (x-y)\vec{j} + (y+z)\vec{k}$  moves a particle from  $A(1, 0, 1)$  to  $B(2, 1, 2)$  along line  $AB$ . Find the workdone. 6

(b) Find the complex form of Fourier series  $f(x) = \sinh x$   $(-\ell, \ell)$  6

(c) Solve the differential equation using Laplace Transform.  
 $(D^2+2D+5)y = e^{-t} \sin t$   $y(0) = 0$   $y'(0) = 1$  8

6. (a) If  $\int_0^{\infty} e^{-2t} \sin(t+\alpha) \cos(t-\alpha) dt = \frac{3}{8}$  find the value of  $\alpha$ . 6

(b) Evaluate  $\iint_s (y^2z^2\vec{i} + z^2x^2\vec{j} + z^2y^2\vec{k}) \cdot \vec{n} ds$  where  $s$  is the hemisphere  $x^2+y^2+z^2=1$  above  $xy$ - plane and bounded by this plane. 6

(c) Find Half range sine series for  $f(x) = \ell x - x^2$   $(0, \ell)$  8

Hence prove that  $\frac{1}{1^6} + \frac{1}{3^6} + \dots = \frac{\pi^6}{960}$